

32 x 32 Enigma 500-3150 MHz Distributive Switch Matrix / Router

4th generation Enigma matrix with enhanced RF performance including variable gain -5 dB to +5 dB settable per output.

500 - 3150 MHz

operating frequency range

Suitable for HTS applications

due to extended bandwidth

Compact

up to 32 inputs x 32 outputs
in a 6U high chassis

Upgraded local control & monitoring

via front panel capacitive touchscreen

Expansion

in single increments or with additional matrix
modules for larger systems

Self diagnostics

with continuous monitoring
of amplifiers, CPUs & PSUs

Resilience

from dual redundant power supplies & CPU modules

Minimal impact from failure

with hot-swap single input & output
RF cards, dual power supplies & dual
CPUs, fans

Dry contact alarm port

for amplifier & power supply status

Future proof secure protocols

with SNMPv3 & HTTPS

Remote control & monitoring

via RJ45 Ethernet port with SNMP & web
browser interface

RF Parameters					
Capacity		32 inputs x 32 outputs, fully populated			
Routing		Distributive, non-blocking. Any input can be connected to any number of outputs.			
Frequency Range		500-3150 MHz			
Gain		0±1 dB Typical, mean across band			
Gain Control		-5 to +5 dB in 0.25 dB steps . Settable at each output.			
RF Connectors		50Ω SMA	50Ω BNC	75Ω BNC	75Ω F-type
		All ports DC blocked			
Gain Flatness	850-2450 MHz	±1.25 dB	±1.25 dB	±1.5 dB	±1.5 dB
	500-3150 MHz	±2.5 dB	±2.5 dB	±2.5 dB	±2.5 dB
Any 36MHz	< 2150 MHz	±0.25 dB	±0.25 dB	±0.5 dB	±0.5 dB
	> 2150 MHz	±0.6 dB	±0.6 dB	±0.75 dB	±0.75 dB
Input Return Loss	Typical	20 dB	20 dB	14 dB	14 dB
	Min <2450MHz	16 dB	14 dB	10 dB	10 dB
	Min >2450MHz	14 dB	14 dB	8 dB	8 dB
Output Return Loss	Typical	18 dB	18 dB	16 dB	16 dB
	Min <2450MHz	16 dB	14 dB	10 dB	10 dB
	Min >2450MHz	14 dB	14 dB	8 dB	8 dB
Isolation (Min. between any 2 ports)	Input-Output	60 dB <2450 MHz		55 dB >2450 MHz	
	Input-Input	75 dB			
	Output-Output	75 dB			
Noise Figure		<2450 MHz	>2450 MHz	With one input routed to one output.	
	Minimum Gain	18 dB Typ	20 dB Typ		
	Unity Gain	16 dB Typ	18 dB Typ		
	Maximum Gain	16 dB Typ	16 dB Typ		
1dB GCP (dBm)	Minimum Gain	3 dBm Min	1 dBm Min	1dB Gain Compression point, output power	
	Unity Gain	8 dBm Min	6 dBm Min		
	Maximum Gain	12 dBm Min	10 dBm Min		
OIP3	Minimum Gain	16 dBm Min	10 dBm Min		
	Unity Gain	20 dBm Min	14 dBm Min		
	Maximum Gain	24 dBm Min	20 dBm Min		
OIP2	Typical	32 dBm Min			
	Minimum	30 dBm Min			
Group Delay		≤ 1.2 ns, across operational bandwidth			
Switching Time		< 50ms from receipt of a command to implementation of path change			
Input RF Power		+ 20 dBm		Absolute maximum	

System Control			
Local Control		Via Front Panel capacitive touchscreen	
Remote Control & Monitoring		Ethernet port via RJ45 10BaseT/100 BaseTx. TCP/IP, SNMPv3, HTTPS & Web browser interface.	
Alarms		Ethernet (RJ45) & Dry contact (D-type) for PSU & Amp. status	
Power			
PSU Power		85-264Vac 50-60Hz	Fused 2A
AC Consumption		150W	Max. consumption at steady state
PSU		Dual redundant & alarmed	Diode OR. Hot swappable
Hot-swap PSU		Yes	
CPU		Dual redundant	Hot swappable
Input cards		Hot swap	Failure affects only one input port
Output cards		Hot swap	Failure affects only one output port
MTTR		20 mins, 15 mins to retrieve spare part and 5 mins to replace	Applies to LRUs only and assumed in house stock
MTBF	Chassis	271,444	Chassis excludes HMI & RF cards
	Switch card	270,297	
	Divider card	317,227	
Environmental			
Operating temperature		0 to 45°C	
Gain Stability versus Temperature		0.05dB/°C	
Storage temperature		-20°C to +75°C	
Location		Indoor use only	
Humidity		20 to 90% non-condensing	
Altitude (operational)		10,000 feet AMSL (Above Mean Sea Level)	
Altitude (storage)		30,000 feet AMSL (Above Mean Sea Level)	
Physical			
Dimensions		6U high x 450mm deep x 19" wide	
Weight		35 kg, fully populated	
Colour		RAL9003—White (Semi-Matte)	

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.
Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.